

Application Report

OPA2365-Q1

Functional Safety FIT Rate and Pin FMA



Table of Contents

1 Overview	2
2 Functional Safety Failure In Time (FIT) Rates	3
3 Pin Failure Mode Analysis (Pin FMA)	4

Trademarks

All other trademarks are the property of their respective owners.

1 Overview

This document contains information for OPA2365-Q1 (SOIC-8 package) to aid in a functional safety system design. Information provided are:

- Functional Safety Failure In Time (FIT) rates of the semiconductor component estimated by the application of industry reliability standards
- Pin failure mode analysis (Pin FMA)

OPA2365-Q1 shows the device functional block diagram for reference.




Figure 1-1. Functional Block Diagram

OPA2365-Q1 was developed using a quality-managed development process, but was not developed in accordance with the IEC 61508 or ISO 26262 standards.

2 Functional Safety Failure In Time (FIT) Rates

This section provides Functional Safety Failure In Time (FIT) rates for OPA2365-Q1 based on two different industry-wide used reliability standards:

- [Table 2-1](#) provides FIT rates based on IEC TR 62380 / ISO 26262 part 11
- [Table 2-2](#) provides FIT rates based on the Siemens Norm SN 29500-2

Table 2-1. Component Failure Rates per IEC TR 62380 / ISO 26262 Part 11

FIT IEC TR 62380 / ISO 26262	FIT (Failures Per 10 ⁹ Hours)
Total Component FIT Rate	10
Die FIT Rate	3
Package FIT Rate	7

The failure rate and mission profile information in [Table 2-1](#) comes from the Reliability data handbook IEC TR 62380 / ISO 26262 part 11:

- Mission Profile: Motor Control from Table 11
- Power dissipation: 120 mW
- Climate type: World-wide Table 8
- Package factor (λ_3): Table 17b
- Substrate Material: FR4
- EOS FIT rate assumed: 0 FIT

Table 2-2. Component Failure Rates per Siemens Norm SN 29500-2

Table	Category	Reference FIT Rate	Reference Virtual T _J
4	Bipolar Op Amp, Comparators, Voltage Monitors	8 FIT	45°C

The Reference FIT Rate and Reference Virtual T_J (junction temperature) in [Table 2-2](#) come from the Siemens Norm SN 29500-2 tables 1 through 5. Failure rates under operating conditions are calculated from the reference failure rate and virtual junction temperature using conversion information in SN 29500-2 section 4.

3 Pin Failure Mode Analysis (Pin FMA)

This section provides a Failure Mode Analysis (FMA) for the pins of the OPA2365-Q1. The failure modes covered in this document include the typical pin-by-pin failure scenarios:

- Pin short-circuited to Ground (see [Table 3-2](#))
- Pin open-circuited (see [Table 3-3](#))
- Pin short-circuited to an adjacent pin (see [Table 3-4](#))
- Pin short-circuited to V+ (see [Table 3-5](#))

[Table 3-2](#) through [Table 3-5](#) also indicate how these pin conditions can affect the device as per the failure effects classification in [Table 3-1](#).

Table 3-1. TI Classification of Failure Effects

Class	Failure Effects
A	Potential device damage that affects functionality
B	No device damage, but loss of functionality
C	No device damage, but performance degradation
D	No device damage, no impact to functionality or performance

[Figure 3-1](#) shows the OPA2365-Q1 pin diagram. For a detailed description of the device pins please refer to the *Pin Configuration and Functions* section in the OPA2365-Q1 data sheet.




Figure 3-1. Pin Diagram

Following are the assumptions of use and the device configuration assumed for the pin FMA in this section:

- Total supply voltage of 5 V with V+ connected to 5V and V- connected to ground
- Input and output pins biased to 2.5 V reference point
- Device is configured with feedback network in gain greater than or equal to 1 V/V

Table 3-2. Pin FMA for Device Pins Short-Circuited to Ground

Pin Name	Pin No.	Description of Potential Failure Effect(s)	Failure Effect Class
1	VOUTA	May cause device to overheat.	B
2	-IN A	Input at V- (GND) is valid input, however, desired application result is unlikely.	C
3	+IN A	Input at V- (GND) is valid input, however, desired application result is unlikely.	C
4	V-	Normal operation, unless dual supply voltage was intended.	D
5	+IN B	Input at V- (GND) is valid input, however, desired application result is unlikely.	C
6	-IN B	Input at V- (GND) is valid input, however, desired application result is unlikely.	C
7	VOUTB	May cause device to overheat.	B
8	V+	Diodes from input to V+ may turn on due to input signal and cause electrical overstress (EOS).	A

Table 3-3. Pin FMA for Device Pins Open-Circuited

Pin Name	Pin No.	Description of Potential Failure Effect(s)	Failure Effect Class
1	VOUTA	Output can be left open. There is no effect on the IC, but the output will not be measured.	C
2	-IN A	Floating input, circuit will likely not function as expected.	C
3	+IN A	Floating input, circuit will likely not function as expected.	C
4	V-	Lowest voltage pin will try to power the device's V- pin.	B
5	+IN B	Floating input, circuit will likely not function as expected.	C
6	-IN B	Floating input, circuit will likely not function as expected.	C
7	VOUTB	Output can be left open. There is no effect on the IC, but the output will not be measured.	C
8	V+	Highest voltage output pin will try to power internal V+	B

Table 3-4. Pin FMA for Device Pins Short-Circuited to Adjacent Pin

Pin Name	Pin No.	Shorted to	Description of Potential Failure Effect(s)	Failure Effect Class
1	VOUTA	-IN A	Channel 1 configured in unity gain	C
2	-IN A	+IN A	No damage to device. Application circuit will not work.	C
3	+IN A	V-	Input at V- (GND) is valid input, however, desired application result is unlikely.	C
4	V-	+IN B	Input at V- (GND) is valid input, however, desired application result is unlikely. Pins are not adjacent to each other.	C
5	+IN B	-IN B	No damage to device. Application circuit will not work	C
6	-IN B	VOUTB	Channel 1 configured in unity gain	C
7	VOUTB	V+	May cause device to overheat.	B
8	V+	VOUTA	May cause device to overheat. Pins are not adjacent to each other.	B

Table 3-5. Pin FMA for Device Pins Short-Circuited to VS+

Pin Name	Pin No.	Description of Potential Failure Effect(s)	Failure Effect Class
1	VOUTA	May cause device to overheat.	B
2	-IN A	Input at V+ is a valid input, however, desired application result is unlikely.	C
3	+IN A	Input at V+ is a valid input, however, desired application result is unlikely.	C
4	V-	Diodes from input to V- may turn on due to input signal and cause electrical overstress (EOS).	A
5	+IN B	Input at V+ is a valid input, however, desired application result is unlikely.	C
6	-IN B	Input at V+ (GND) is a valid input, however, desired application result is unlikely.	C
7	VOUTB	May cause device to overheat.	B
8	V+	Normal Operation.	D

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2022, Texas Instruments Incorporated